TITLE: DUAL FEEDBACK CONTROL SYSTEM FOR MAINTAINING
          THE TEMPERATURE OF AN IC-CHIP NEAR A SET-POINT

BACKGROUND OF THE INVENTION:

Complex IC-chips (integrated circuit chips) are subjected to several tests as they are manufactured to both determine their functionality and to insure their
5   future reliability. A "wafer" test is usually performed first. During this test, individual IC-chips in the wafer are probed. This is a quick test in which only certain types of defects in the IC-chips are detected. Thermal control during the wafer test is typically
10 achieved simply with a cold plate that contacts the wafer.
The next test, which takes place after the IC-chips ar packag d, is called "burn-in". The burn-in test thermally and electrically stresses the IC-chips to
15 accelerate "infant mortality" failures. The stressing

cjf\appl\550707.doc

causes immediate failures that oth rwise would occur during the first 10% of the IC-chips' life in the field, thereby insuring a more reliable product for the customer. The burn-in test can take many hours to

5 perform, and the temperature of the IC-chip typically is held in the 100°C to 140°C range. Because the IC-chips are also subjected to higher than normal voltages, the power dissipation in the IC-chip can be significantly higher than in normal operation. This extra power

10 dissipation makes the task of controlling the temperature of the IC-chip very difficult. Further, in order to minimize the time required for burn-in, it is also desirable to keep the temperature of the IC-chip as high as possible without damaging the IC-chip.

15 A "class" test usually follows the burn-in test. Here, the IC-chips are speed sorted and the basic function of each IC-chip is verified. During this test, power dissipation in the IC-chip can vary wildly as the IC-chip is sent a stream of test signals. Because the

20 operation of an IC-chip slows down as the temperature of the IC-chip increases, very tight temperature control of the IC-chip is required throughout the class test. This insures that the speed at which the IC-chip operates is measured precisely at a specified temperature. If the

25 IC-chip temperature is too high, the operation of the IC-chip will get a slower speed rating. Then the IC-chip will be sold as a lower priced part.

In the prior art, the present inventors have already disclosed a system which will maintain the

30 temperature of an IC-chip at a set-point as the IC-chip undergoes the abov described "burn-in" test and "class"

cjf\appl\550707.doc

test.   This prior art system is disclosed in US pat nt 5,812,505 which is entitled "TEMPERATURE CONTROL SYSTEM FOR AN ELECTRONIC DEVICE WHICH ACHIEVES A QUICK RESPONSE BY INTERPOSING A HEATER BETWEEN THE DEVICE AND A HEAT

5   SINK."   All of the details of that patent are herein incorporated by reference.

However, even though the system of patent ˋ505 does in fact control the temperature of an IC-chip very accurately, the present inventors have now discovered one

10   particular technical drawback with that system.   This drawback has nothing to do with the accuracy at which the temperature of the IC-chip is maintained, and it is explained   herein   in   the   Detailed   Description   in conjunction with Figs. 5-10.

15   Accordingly, the primary object of the present invention is to provide a novel temperature control system for an IC-chip which addresses and solves a technical drawback in system of patent ˋ505.

BRIEF SUMMARY OF THE INVENTION:

The present invention is a dual feedback
control system for maintaining the temperature of an IC-
chip near a set-point while the IC-chip dissipates a
5   varying amount of electrical power. This system includes
an evaporator for a liquid refrigerant and an electric
heater which has one face connected to the evaporator and
an opposite face for contacting the IC-chip. Also, this
system includes an evaporator controller coupled to the
10   evaporator, and a heater controller coupled to the
electric heater. Further, the heater controller includes
a first feedback circuit which sends electrical power to
the electric heater with a variable magnitude that
compensates for changes in the electrical power which the
15   IC-chip dissipates. In addition, the evaporator
controller includes a second feedback circuit which
passes the liquid refrigerant into the evaporator with a
variable flow rate that reduces electrical power usage in
the heater over the power usage which otherwise occurs if
20   the flow rate of the refrigerant is fixed.

Two numerical examples, which illustrate the
magnitude of the power savings that is achieved with the
second feedback circuit, are provided herein in Figs. 5-
10. In the example of Figs. 5-7, electrical power usage
25   in the heater is reduced by 61%. In the example of Figs.
8-10, electrical power usage in the heater is reduced by
66%. This power savings is in comparison to the above
referenced prior art temperature control system of U.S.
patent 5,821,505.

30   In on particular embodiment, the s cond
fe dback circuit senses th instantaneous pow r to the

cjf\appl\550707.doc

el ctric h ater. Then the second feedback circuit sends the liquid refrigerant to the evaporator with a flow rate that -a) decreases if the average of the sensed power to the electric heater over a certain time interval is above

5   an upper power limit, and b) increases if the average over the time interval is below a lower power limit.

In another particular embodiment, the second feedback circuit senses the temperature of the evaporator. Then the second feedback circuit sends the

10   liquid refrigerant to the evaporator with a flow rate that -a) decreases if the set-point minus the temperature of the evaporator is more than a maximum difference, and b) increases if the set-point minus the temperature of the evaporator is less than a minimum difference.

BRIEF DESCRIPTION OF THE DRAWINGS:

Fig. 1 shows a dual feedback control system for maintaining the temperature of an IC-chip near a set-point, which is one preferred embodiment of the present invention.

5

Fig. 2 is a schematic diagram that shows where electrical power and thermal power flow through the system of Fig. 1.

Fig. 3 is the same as the schematic diagram of Fig. 2 except that various items in Fig. 3 are assigned numerical values.

10

Fig. 4 shows a set of equations which determine the power to the heater in the schematic diagram of Fig. 3.

Fig. 5 is the same as the schematic diagram of Fig. 3 except that the power which the IC-chip dissipates in Fig. 5 is decreased from 150 watts to 70 watts.

15

Fig. 6 is a set of equations which determine the pow r to the h ater in the schematic diagram of Fig. 5.

20

Fig. 7 is a set of equations which determine the power to the heater in the schematic diagram of Fig. 5 under the condition where the evaporator control circuit in Fig. 1 changes the temperature of the

5   evaporator from -5°C to +7°C.

Fig. 8 is the same as the schematic diagram of Fig. 3 except that the set-point for the IC-chip is raised from 25°C to 40°C.

Fig. 9 is a set of equations which determine

10   the power to the heater in the schematic diagram of Fig. 8.

Fig. 10 is a set of equations which determine the power to the heater in the schematic diagram of Fig. 8 under the condition where the evaporator control

15   circuit of Fig. 1 changes the temperature of the evaporator from -5°C to +10°C.

Fig. 11 is a diagram which shows how the heater control circuit in Fig. 1 and the evaporator control circuit in Fig. 1 operate over time.

20   Fig. 12 shows one preferred embodiment of the internal structur of the vaporator control circuit in Fig. 1.

cjf\appl\550707.doc

DETAILED DESCRIPTION:

A dual feedback control system for maintaining the temperature of an IC-chip near a set-point, which is one preferred embodiment of the present invention, will

5   now be described in conjunction with Fig. 1. In that figure, item 10 is the IC-chip whose temperature is being maintained, and item 11 is a substrate on which the IC-chip is attached. All of the remaining components in Fig. 1 comprise the dual feedback control system, and

10   these components are identified below in TABLE 1.

TABLE 1

Component	Description
20	Component 20 is a thin, flat electric heater. The heater 20 has one flat face which contacts the IC-chip 10, and it has an opposite flat face which is connected directly to component 21. Electrical power P_H is sent to the heater 20 on conductors 20a. The temperature of the heater 20 is detected by a sensor 20b in the heater 20. This temperature is indicated by a signal ST_H on conductors 20c.

21 . . . . . . Component 21 is an evaporator for a refrigerant. The refrigerant enters the evaporator 21 in a liquid state through a conduit 21a, and the refrigerant exits the evaporator 21 in a gas state through a conduit 21b. The temperature of the evaporator 21 is detected by a sensor 21c on the exterior of the evaporator. This temperature is indicated by a signal ST_E on conductors 21d.

22 . . . . . . Component 22 is a valve which receives the refrigerant in a liquid state from a conduit 22a, and which passes that refrigerant at a selectable flow rate to the conduit 21a. The flow rate through the valve 22 is selected by a control signal SF_V on conductors 22b. In one embodiment, the signal SF_V is a pulse modulated signal, and the valve 22

opens for th duration of each pulse. In another embodiment, the signal SF_V is an amplitude modulated analog signal, and the valve 22 opens to a degree that is proportional to the amplitude of the signal.

23 . . . . . . Component 23 is a compressor-condenser which has an input that is connected to conduit 21b, and an output that is connected to conduit 22a. The compressor-condenser 23 receives the refrigerant in the gas state, and then compresses and condenses that refrigerant to the liquid state.

24 . . . . . . Component 24 is a socket which holds the substrate 11. Electrical conductors 24a, 24b and 24c pass through the socket to the IC-chip 10. The conductors 24a carry test signals to and from the IC-chip 10. The conductors 24b carry electrical pow r P_E to the IC-chip 10. The conductors

24c carry signals ST_C which indicate the temperature of the IC-chip 10. These signals ST_C are generated by a temperature sensor 10a that is integrated into the IC-chip 10.

25 . . . . . . Component 25 is a power supply which sends the power P_H to the electric heater 20 with a selectable magnitude. The amount of power that is sent at any instant is selected by a signal SP_H on conductors 25a.

26 . . . . . . Component 26 is a control circuit for the heater power supply 25. This control circuit 26 generates the signal SP_H on the conductors 25a in response to the signals ST_E, ST_H, ST_C, and SP which it receives on the conductors 21d, 20c, 24c and 26a. The signal SP indicates a set-point temperature at which the IC-chip 10 is to be maintained. The control circuit 26, tog th r with

5

10

15

20

25

30

the pow r supply 25 and the electric heater 20, form a first feedback loop in the Fig. 1 control system.

5 This first feedback loop quickly compensates for changes in power dis-sipation in the IC-chip 10 and thereby maintains the

10 temperature of the IC-chip 10 near the set-point.

27 . . . . . . Component 27 is a control circuit for the valve 22. This control circuit 27

15 generates the signal SF_V on the conductors 22b in response to the signals SP_H, ST_E, and SP which it receives on the conductors

20 25a, 21d, and 26a. The control circuit 27, together with the valve 22 and the evaporator 21, form a second feedback loop in

25 the Fig. 1 control system. This second feedback loop passes the liquid refrigerant through the evaporator with a variable

30 flow rat that reduc s the

ov rall usage of electrical power in the Fig. 1 system.

Next, with reference to Figs. 2-11, additional details will be described on how the first and second

5 feedback loops operate. To begin, reference should be made to Fig. 2 which is a schematic diagram that shows where electrical power and thermal power flow through the Fig. 1 system in the steady state. Several symbols are used in Fig. 2, and those symbols are defined below in

10 TABLE 2.

TABLE 2

Symbol	Meaning
P_C	P_C is the instantaneous electrical power that is sent to the IC-chip 10. This power varies in a random manner in response to the TEST signals in Fig. 1. This power also varies in proportion to the DC voltage level at which the power is sent. The DC voltage level can be increased above a normal level, during some tests, in order to catch certain types of failures in the IC-chip 10.

P_H . . . . . . P_H is the instantaneous electrical power that is sent to the heater 20.

T_C . . . . . . T_C is the instantaneous
5   temperature of the IC-chip 10.

T_H . . . . . . T_H is the instantaneous temperature of the heater 20.

10   T_E . . . . . . T_E is the instantaneous temperature of the evaporator 21.

$\theta(C-H)$ . . . . $\theta(C-H)$ is the thermal resistance between the IC-
15   chip 10 and the heater 20.

$\theta(H-E)$ . . . . $\theta(H-E)$ is the thermal resistance between the heater 20 and the evaporator 21.

20   In the steady-state (which is shown in Fig. 2) T_C is at the set-point temperature, and the temperatures T_H and T_E are progressively colder. Also in the steady-state, thermal power flows from the IC-chip 10 to the refrigerant along the path 31, and thermal power flows
25   from the heater 20 to the refrigerant along the path 32. Further in the steady-state, the thermal power on path 31 equals the electrical power P_C that is sent to the IC-chip 10, and the th rmal pow r on path 32 equals the electrical pow r P_H that is s nt to the heat r 20.

Suppos now that P_C incr ases to a higher l vel $P_C(+)$. Then, in response, T_C will tend to rise above the set-point. But to compensate for that effect, the heater control circuit 26 will decrease P_H. In response, T_H will
5   drop, and that will keep the IC-chip 10 at the set-point while it dissipates the higher level of power $P_C(+)$.

Conversely, suppose that P_C decreases to a lower power level $P_C(-)$. Then in response, T_C will tend to drop below the set-point. But to compensate for that effect,
10   the heater control circuit 26 will increase P_H. In response, T_H will rise, and that will keep the IC-chip 10 at the set-point while it dissipates the decreased level of power $P_C(-)$.

A numerical example of how to determine the
15   particular heater power P_H which will keep T_C at the set-point, under steady-state conditions, is shown in Figs. 3 and 4. In Fig. 3, the IC-chip 10 is at a set-point of 25°C, and the temperature of the evaporator is -5°C. Also in Fig. 3, the thermal resistances $\theta(C-H)$ and $\theta(H-E)$ are
20   0.1°C/W, and 0.05°C/W respectively.

The particular heater power P_H which will keep the IC-chip 10 at the set-point in Fig. 3 is calculated by equations 1-4 in Fig. 4. Equation 1 says that the temperature drop from T_C to T_E is equal to P_C times all of
25   the thermal resistance in path 31, plus P_H times all of the thermal resistance in path 32. Then equation 2 is obtained by substituting numerical values from Fig. 3 into equation 1. Next equation 3 is obtained by adding and subtracting the various numerical values that occur
30   in equation 2. Then equation 4 is obtained by solving

equation 3 for the heater pow r P_H. From equation 4, th heater power P_H is calculated to be 150 watts.

Now, suppose that the IC-chip power P_C decreases from 150 watts as shown in Fig. 3 to 70 watts as shown in

5   Fig. 5. When that occurs, the power P_H to the electric heater must increase in order to keep the temperature of the IC-chip 10 at the set-point. The particular heater power P_H which keeps the IC-chip 10 at the set-point in the steady-state is calculated by equations 10-12 in Fig.

10   6.

Equation 10 says that the temperature drop from T_C to T_E is equal to P_C times the thermal resistance in path 31, plus P_H times the thermal resistance in path 32. Then equation 11 is obtained by adding and subtracting

15   the various numerical values that occur in equation 10. Then equation 12 is obtained by solving equation 11 for the heater power P_H. From equation 12, the heater power P_H is calculated to be 390 watts.

If the above drop in IC-chip power from 150

20   watts to 70 watts is just a transient that occurs as part of the random changes in P_C due to the TEST signals, then the evaporator control circuit 27 does nothing in response. Conversely, if the average of the heater power during a predetermined interval ΔT stays at 390 watts,

25   then the evaporator control circuit 27 responds by lowering the flow rate of the refrigerant to the evaporator 21, which raises the temperature T_E of the evaporator 21.

Raising T_E makes the operation of the Fig. 1

30   system more effici nt. A num rical example of this is shown by equations 13-16 of Fig. 7.

cjf\appl\550707.doc

Equation 13 says that T_E is rais d from $-5°C$ to $+7°C$. The evaporator control circuit 27 does this by generating the signal SF_V in Fig. 1 such that the flow rate of the refrigerant through the valve 22 is reduced.

5   As that flow rate drops, the temperature T_E increases because less refrigerant changes from a liquid to a gas in the evaporator 21.

Equation 14 says that the temperature drop from T_C to T_E is equal to P_C times the thermal resistance in

10 path 31, plus P_H times the thermal resistance in path 32. Then equation 15 is obtained by adding and subtracting the various numerical values that occur in equation 14. Then, equation 16 is obtained by solving equation 15 for the heater power P_H. From equation 16, the heater power

15 P_H is calculated to be 150 watts.

Comparing equation 16 with equation 12 indicates that 240 watts are saved due to the operation of the evaporator control circuit 27. In other words, the second control loop in the Fig. 1 system reduces

20 electrical power consumption in the heater 20 from 390 watts to 150 watts, or 61%.

Also in the Fig. 1 system, the compressor-condenser 23 must work harder as the heater power is increased. Thus, additional power is saved by the

25 compressor-condenser when the heater power is only 150 watts, as compared to being 390 watts.

In the prior art temperature control system of U.S. patent 5,812,505 (which is referenced herein in the BACKGROUND), there is no second control loop. In the

30 ˜505 system, liquid coolant flows through a heatsink at a constant flow rate and a constant temp ratur . Thus when

the IC-chip power drops from 150 watts to 70 watts in the
`505 system, the electrical power which is sent to the
heater to compensate for that drop is determined by
equations 10-12 in Fig. 6.

5   Next, suppose that the system of Fig. 1 is
again operating under the previously described steady-
state conditions that are shown in Fig. 3.   Then,
consider what happens if the set-point temperature is
increased from 25°C to 40°C.   When that change in set-
10   point occurs, the steady-state operation that is shown in
Fig. 5 changes to the steady-state operation that is
shown in Fig. 8.

The particular heater power P_H in Fig. 8 which
will keep the IC-chip 10 at the set-point in the steady-
15   state is calculated by equations 20-22 in Fig. 9.
Equation 20 says that the temperature drop from T_C to T_E
is equal to P_C times the thermal resistance in path 31,
plus P_H times the thermal resistance in path 32.   Then
equation 21 is obtained by adding and subtracting the
20   various numerical values that occur in equation 20.   Then
equation 22 is obtained by solving equation 21 for the
heater power P_H.   From equation 22, the heater power P_H is
calculated to be 450 watts.

The above rise in heater power from 150 watts
25   in Fig. 3 to 450 watts in Fig. 8 is not just a transient
that occurs as part of the random changes in P_C due to the
TEST signals.   Thus the evaporator control circuit 27
responds by raising the temperature T_E of the evaporator
21 to again make the operation of the Fig. 1 system more
30   ffici nt.   A numerical example of this is shown by
quations 23-26 of Fig. 10.

cjf\appl\550707.doc

Equation 23 says that T_E is rais d from $-5°C$ to $+10°C$. The evaporator control circuit 27 does this by generating the signal SF_V in Fig. 1 such that the flow rate of the refrigerant through the valve 22 is reduced. Equation 24 says that the temperature drop from T_C to T_E is equal to P_C times the thermal resistance in path 31, plus P_H times the thermal resistance in path 32. Next equation 25 is obtained by adding and subtracting the various numerical values that occur in equation 24. Then equation 26 is obtained by solving equation 25 for the heater power P_H. From equation 26, the heater power P_H is calculated to be 150 watts.

Comparing equation 26 with equation 22 indicates that 300 watts are saved due to the operation of the evaporator control circuit 27. Thus, the second control loop in the Fig. 1 system reduced electrical power consumption in the heater 20 from 450 watts to 150 watts, or 66%. Here again, additional power is also saved by the compressor-condenser 23 since it does not have to work as hard when the heater power is only 150 watts instead of being 450 watts.

By comparison, in the prior art temperature control system of U.S. patent 5,812,505, liquid coolant flows through a heatsink at a constant flow rate and a constant temperature. Thus when the set-point rises from 25°C to 40°C in the ˜505 system, the electrical power which is sent to the heater to compensate for that rise is determined by equations 20-22 in Fig. 9.

Next, reference should be made to Fig. 11 which shows how the heat r control circuit 26 and the evaporator control circuit 27 op rat over time. In Fig.

11, tim increases from left to right on the horizontal
axis. Also in Fig. 11, a waveform 41 illustrates the
running average of the power that is. sent to the heater
20. This average at any time t is taken during a time
5   interval ΔT that ends at time t.

Further in Fig. 11, a waveform 42 illustrates
the instantaneous power that is sent to heater 20. This
instantaneous power is rapidly increased by the heater
control circuit 26 when T_C starts to fall below the set-
10   point, and it is rapidly decreased when T_C starts to rise
above the set-point. Consequently, T_C always stays at, or
near, the set-point.

To simplify Fig. 11, the instantaneous heater
power as indicated by waveform 42 is shown only from time
15   t1 to time t2; whereas the average heater power as
indicated by waveform 41 is shown from time t1 to time
t9. It is to be understood that the rapid changes in
waveform 42 are superimposed on waveform 41 from time t2
to time t9, just like they are from time t1 to time t2.

20   Further in Fig. 11, reference numerals 43 and
44 respectively illustrate an upper limit and lower limit
for the average heater power. Signals which represent
the two limits 43 and 44 are stored within the evaporator
control circuit 27.

25   When the average heater power 41 rises above
the upper limit 43, then the evaporator control circuit
27 decreases the flow-rate F_R of the refrigerant to the
evaporator 21. Conversely, when the average heater power
41 drops below the lower limit 44, then the evaporator
30   control circuit 27 incr ases th flow rate F_R of the

refrigerant to the evaporator 21. The flow rate F_R is shown by waveform 45 in Fig. 11.

From time t1 to time t2 in Fig. 11, the average heater power 41 stays within the limits 43 and 44. Thus

5 the evaporator control circuit 27 makes no change to the flow rate F_R.

Then, at time t2, a step increase occurs in the set-point temperature. Thus a large difference occurs between the set-point temperature and the temperature T_C

10 of the IC-chip 10. In response, the heater control circuit 26 increases the average power 41 to the heater 20.

Also, the evaporator control circuit 27 reacts to step changes in the set-point temperature.

15 Specifically, the evaporator control circuit 27 sends the liquid refrigerant to the evaporator 21 with a flow rate that -a) decreases if the set-point minus the temperature of the evaporator 21 steps above an upper limit, and b) increases if the set-point minus the temperature of the

20 evaporator 21 steps below a lower limit. One suitable upper limit is 50°C, and one suitable lower limit is 30°C.

In Fig. 11, the evaporator control circuit 27 decreases the flow rate F_R of refrigerant as shown by waveform 45 from time t2 to time t3. As the flow rate F_R

25 decreases, the temperature T_E of the evaporator increases. Thus a decrease occurs in the average heater power 41 which is required to keep the IC-chip 10 at the set-point, in the steady-state.

At time t3, the average heater power 41 falls

30 below th upper limit 43. When that occurs, the

vaporator control circuit 27 stops changing the flow rate F_R of the refrigerant.

From time t3 to time t4, the average heater power 41 slowly drops from the upper limit 43 to the lower limit 44. This indicates that the flow rate F_R that was set at time t3 is too low.

Thus from time t4 to time t5, the evaporator control circuit 27 reacts by increasing the flow rate F_R as shown by waveform 45. This lowers the temperature T_E of the evaporator 21. In response, the heater control circuit 26 increases the average heater power 41 in order to keep the IC-chip 10 at the set-point SP in the steady-state.

At time t5, the average heater power 41 rises above the lower limit 44. When that occurs, the evaporator control circuit 27 stops changing the flow rate F_R of the refrigerant.

Thereafter, from time t5 to time t6, the average heater power 41 stays within the two limits 43 and 44. Thus no change occurs in the flow rate F_R.

Next, at time t6, a step decrease occurs in the average power P_C to the IC-chip 10. This can be caused by a step decrease in the DC voltage at which the power is sent to the IC-chip 10. This also can be caused by a change from one sequence of TEST signals to another sequence of TEST signals which switches fewer transistors within the IC-chip 10.

In response to the above power decrease, the temperature of the IC-chip 10 starts to drop below the set-point. That temperatur drop is sensed by the h·a2eXe control circuit 26 which reacts by quickly incr asing the average heater power 41.

When the averag heat r power 41 rises above the upper limit 43, the evaporator control circuit 27 responds by decreasing the flow rate F_R of the refrigerant. This is shown by waveform 45 from time t6

5　to time t7. Due to that decreased flow rate, the temperature of the evaporator 21 increases. This increased evaporator temperature allows the average heater power 41 to be lowered and still maintain the IC-chip 10 at the set-point in the steady-state.

10　　Between time t7 and time t8, the average heater power 41 slowly drops from the upper limit 43 to the lower limit 44. This indicates that the flow rate F_R was set too low at time t7.

　　Thus from time t8 to time t9, the evaporator

15　control circuit 27 reacts by increasing the flow rate F_R as shown by waveform 45. In response, the evaporator temperature T_E decreases. Thus the heater control circuit 26 increases the average heater power 41 in order to keep the IC-chip 10 at the set-point in the steady-state.

20　　At time t9, the average heater power 41 rises above the lower limit 44. When that occurs, the evaporator control circuit 27 stops changing the flow rate F_R. Thereafter, the average heater power 41 stays within the two limits 43 and 44, so the evaporator

25　control circuit 27 makes no change in the flow rate F_R.

　　Next, with reference to Fig. 12, one preferred embodiment of the internal structure of the evaporator control circuit 27 will be described. This Fig. 12 embodiment includes all of the components 51-66, and

30　those components are identifi d b low in TABLE 3.

TABLE 3

Component	Description
51	Component 51 is a register which holds digital signals that specify the upper limit for the average heater power. Suitably, this upper limit is 250 watts as one example, as shown in Fig. 12. Preferably, the upper limit is at least twice the lower limit.
52	Component 52 is a register which holds digital signals that specify the lower limit for the average heater power. Preferably, this lower limit is not less than 50 watts, as shown in Fig. 12.
53	Component 53 is a register which holds digital signals that specify the time period ΔT during which the running average of the heater power is determined. Preferably, this time period is in the range of 0.5 to 10 s conds.

5

10

15

20

25

30

54 . . . . . . Compon nt 54 is a circuit which determines the running average of the heater power. An output signal S1 from circuit 54 indicates this average. One particular embodiment of circuit 54 is a digital low pass filter which samples the instantaneous heater power during the time interval ΔT.

55 . . . . . . Component 55 is an arithmetic circuit which subtracts its negative input from its positive input. An output signal S2 from circuit 55 indicates this difference.

56a,56b. . . . Components 56a and 56b respectively are a diode and a resistor which together generate a signal S3. The signal S3 equals the signal S2 when the signal S2 is greater than zero. Otherwise, signal S3 equals zero.

57 . . . . . .   Component 57 is an arithmetic circuit which subtracts its negative input from its positive input. An output signal S4 from circuit 57 indicates this difference.

58a,58b. . . .   Component 58a and 58b respectively are a diode and a resistor which together generate a signal S5. The signal S5 equals the signal S4 when the signal S4 is greater than zero. Otherwise, signal S5 equals zero.

59 . . . . . .   Component 59 is a register which holds digital signals that specify the upper limit for the set-point temperature minus the temperature of the evaporator 21. Preferably, this upper limit does not exceed 50°C, as shown in Fig. 12.

60 . . . . . .   Component 60 is a register which holds digital signals that specify the lower limit for th set-point temperature minus the

temp ratur of the evaporator 21. Preferably, this lower limit is at least 30°C, as shown in Fig. 12.

5

61 . . . . . .   Component 61 is an arithmetic circuit which subtracts its negative input from its positive input. An output signal S6 from circuit 61 indicates this difference.

10

62 . . . . . .   Component 62 is an arithmetic circuit which subtracts its negative input from its positive input. An output signal S7 from circuit 62 indicates this difference.

15

63a, 63b. . . .   Component 63a and 63b respectively are a diode and a resistor which together generate a signal S8. The signal S8 equals the signal S7 when the signal S7 is greater than zero. Otherwise, signal S8 equals zero.

20

25

64 . . . . . .   Component 64 is an arithmetic circuit which subtracts its negative input from its positive input. An output signal S9 from circuit 64 indicates this difference.

65a,65b. . . .   Component 65a and 65b respectively are a diode and a resistor which together generate a signal S10. The signal S10 equals the signal S9 when the signal S9 is greater than zero. Otherwise, signal S10 equals zero.

66 . . . . . .   Component 66 is a circuit which generates the signal SF_V in response to the signals S3, S5, S8 and S10. How this is done is described below.

The operation of the Fig. 12 circuit begins by loading all of the registers 51, 52, 53, 59, and 60 with their parameters. To do this, the registers 51, 52, 53, 59, and 60 are sequentially sent their parameters via a time-shared data bus DB. The particular parameter values are selected by an operator and sent from the operator's terminal (not shown).

Thereafter, the signals SP_H, SP, ST_E are continually rec ived by components 54 and 61. Th n in

response, those signals are continually proc ssed by components 54, 55, 56a, 56b, 57, 58a, 58b, 61, 62, 63a, 63b, 64, 65a, and 65b. In that manner, the signals S3, S5, S8 and S10 are continually generated.

5   Signal S3 indicates the degree to which the flow rate through valve 22 should be decreased when heater power is too high.   Conversely, signal S5 indicates the degree to which the flow rate through valve 22 should be increased when heater power is too low.

10   Signal S8 indicates the degree to which the flow rate through valve 22 should be decreased when the evaporator temperature is too far below the set-point. Conversely, signal S10 indicates the degree to which the flow rate through valve 22 should be increased when the

15   evaporator temperature is too close to the set-point.

          A flow rate increase that is indicated by signal S5 is offset by a flow rate decrease that is indicated by signal S8. Likewise, a flow rate increase that is indicated by signal S10 is offset by a flow rate

20   decrease that is indicated by signal S3.

          When the net of all of the signals S3, S5, S8, and S10 indicates that the flow rate through valve 22 is too low, then circuit 66 changes the signal SF_v in a manner which increases that flow rate. Likewise, when

25   the net of all of the signals S3, S5, S8, and S10 indicates that the flow rate through valve 22 is too high, then circuit 66 changes the signal SF_v in a manner which decreases that flow rate. At all other times, when the signals S3, S5, S8, and S10 are zero, then circuit 66

30   makes no change to the signal SF_v.

          Suitably, the signal SF_v is generated as a pulse modulat d signal which opens valv 22 compl tely for the

time duration of each pulse in the signal. Alternatively, the signal SF_V is generated as an amplitude modulated signal which opens valve 22 to a degree that is proportional to the amplitude of the signal.

5   One preferred embodiment of a dual feedback control system, for maintaining the temperature of an IC-chip near a set-point, has now been described in detail. Now, several modifications which can be made to that embodiment, without departing from the scope of the

10   invention, will be described.

As one modification, the IC-chip 10 whose temperature is being maintained near the set-point can be in any type of "chip-package". In Fig. 1, the IC-chip 10 is shown as being packaged on just the substrate 11.

15   Alternatively, the IC-chip 10 can be "unpackaged" and held directly by the socket 14. Also alternatively, the IC-chip 10 on the substrate 11 can be completely enclosed with a cover. Thus, the heater 20 in Fig. 1 can contact an IC-chip directly or contact a cover which encloses the

20   IC-chip.

As another modification, the IC-chip 10 whose temperature is being maintained near the set-point, can either include or not include its own temperature sensor. In Fig. 1, the IC-chip 10 is shown as including its own

25   temperature sensor 10a. However, if the IC-chip 10 does not have such a temperature sensor, then the heater control circuit 26 can estimate the temperature T_C of the IC-chip 10 by monitoring the temperature of the heater 20 via signal ST_H and the temperature of the evaporator via

30   signal ST_E. How this estimation is p rformed is disclos d by the pres nt inventors in U.S. patent 5,844,208 which is entitled "TEMPERATURE CONTROL SYSTEM FOR AN ELECTRONIC

DEVICE IN WHICH DEVICE TEMPERATURE IS ESTIMATED FROM
HEATER TEMPERATURE AND HEAT SINK TEMPERATURE".

As still another modification, the system of
Fig. 1 can be expanded such that a plurality of N IC-
chips 10 simultaneously have their respective temperature
maintained near a respective set-point. In this expanded
system, all of the components 20-22 and 24-27 are
replicated N times. The compressor-condenser 23 may occur
one or more times, as desired. The refrigerant is sent
in a liquid state from the compressor-condenser(s) 23 to
all of the replicated valves 22, and the refrigerant is
returned in a gas state from all of the replicated
evaporators 21 to the compressor-condenser(s) 23.

Further, as another modification, the
particular evaporator control circuit 27 that is shown in
Fig. 12 can be simplified. One simplification is made by
fixing all of the parameters that are held in the
registers 51, 52, 53, 59, and 60. Those fixed parameters
are then built into components 54, 55, 57, 62, and 64.
This enables all of the registers 51, 52, 53, 59, and 60,
as well as the data bus DB, to be eliminated.

A second simplification to the evaporator
control circuit of Fig. 12 is made by eliminating all of
the components that generate the signals S8 and S10.
These are components 59, 60, 61, 62, 63a, 63b, 64, 65a,
and 65b. With this modification, the electrical power
which is used by the heater 20 is still reduced in
comparison to a system where the flow-rate through the
valve 22 is fixed. However, the power savings may not be
as large as that which is achiev d with the control
circuit of Fig. 12.

cjf\appl\550707.doc

Similarly, a third simplification to th evaporator control circuit of Fig. 12 is made by eliminating all of the components that generate the signals S3 and S5. Those are components 51, 52, 53, 54,

5   55, 56a, 56b, 57, 58a, and 58b. Here again, with this modification, the electrical power which is used by the heater 20 is still reduced in comparison to a system where the flow-rate through the valve 22 is fixed. However, the power savings may not be as large as that

10   which is achieved with the control circuit of Fig. 12.

A fourth simplification to the evaporator control circuit of Fig. 12 is that the upper power limit which is held in register 51 and the lower power limit which is held in register 52 can be the same. In that

15   case, register 52 can be eliminated, and the output of register 51 is sent to the positive input of the arithmetic circuit 57 as well as the negative input of the arithmetic circuit 55. Similarly, the upper limit of the temperature difference which is held in register 59

20   can be the same as the lower limit of the temperature difference that is held in register 60. In that case, register 60 can be eliminated, and the output of register 59 is sent to the positive input of the arithmetic circuit 64 as well as the negative input of the

25   arithmetic circuit 62.

Also, each of the components 51-66 in the evaporator control circuit 27 that are shown in Fig. 12 can be implemented in any desired fashion. For example, each of the arithmetic circuits 55, 57, 61, 62, and 64

30   can b a digital arithm tic circuit which subtracts digital signals, or an analog arithmetic circuit which subtracts analog signals. As another xample, the diode-

resistor pairs 56a-56b, 58a-58b, 63a-63b, and 65a-65b can be implemented as any circuit which passes the signals S2, S4, S7, and S9 when those signals are greater than zero, and otherwise generates a zero output. As still

5 another example, the arithmetic circuits 55, 57, 62, and 64 can be implemented such that they produce a zero output when their negative input is larger in magnitude than their positive input, and then, the diode-resistor pairs 56a-56b, 58a-58b, 63a-63b, and 65a-65b can be

10 deleted.

As another modification, the refrigerant which is used in the Fig. 1 system can be any substance which changes from a liquid phase to a gas phase in the evaporator. For example, these refrigerants can be

15 fluorohydrocarbons such as fluoromethane or fluoroethane, or water, or liquid nitrogen, or any other liquid with suitable evaporative properties.

In view of the above, it is to be understood that the present invention is not limited to all of the

20 details of just one particular embodiment, but is defined by the appended claims.